

SA-A60/SA-A120/SA-A240/SA-A360/SA-A500/SA-A650

6-zone Mixer Amplifier



Features

1. Black brushed panel, 19-inch standard industrial chassis design.
2. 2 mic inputs, 3 line inputs, 1 aux output.
3. Each signal input has independent volume control and total volume adjustment.
4. With treble-bass adjustment function, with 6-zone function, 6-channel separate zone selection switch.
5. With silent strong insertion function, it is easy to insert priority broadcast.
6. Automatic temperature control fan forced cooling.
7. The MIC1 input interface has the highest priority.
8. 70V/100V/4-16Ω output.

Technical parameters

Model	SA-A60	SA-A120	SA-A240	SA-A360	SA-A500	SA-A650
Power	60W	120W	240W	360W	500W	650W
Power consumption	100W	200W	400W	550W	720W	950W
Sensitivity	Line 250mV Microphone 2mV					
Tone	Bass: ±10dB at 100Hz					
	Treble: ±10dB at 10Hz					
Signal to noise ratio	Line 70dB Microphone 66dB					
Output	70V/100V/4-16Ω					
Frequency	100HZ-18KHZ					
Distortion	< 1%					
Input power	AC 220-240V/50-60Hz					
Size	484×366×88mm			484×410×88mm		
Weight	9Kg	10Kg	12Kg	15Kg	17.5Kg	19Kg