

SA-1028 Digital Tuner



Features

1. 19-inch standard cabinet design, humanized design
2. Automatic frequency search and storage function, and power-off memory function
3. 40 FM/AM channels can be stored
4. LCD digital display, support remote control operation, simple and fast
5. Two groups of receiving antenna input: AM receiving antenna input; FM receiving antenna 75Ω input

Technical parameters

Model	SA-1028
Power consumption	25W
Frequency range	MW 522KHz — 1620KHz FM 87MHz — 108MHz
Signal to noise ratio	MW ≥ 40 dB FM ≥ 45 dB
Noise limiting sensitivity	MW ≤ 5 mV/m FM ≤ 20 uV
Power source	AC220V~240V 50/60HZ
Size	484×390×44mm
Weight	4.5kg