

## SA-120U/SA-240U/SA-360U/SA-500U/SA-650U

### Mixer Amplifier With Mp3, Bluetooth And Tuner



#### Features

1. With Bluetooth, FM radio, U disk, TF card and other playback functions
2. Black brushed panel, 2U rack-mountable, 19" industrial chassis design.
3. 3-channel microphone input (TRS terminal), 2-channel line input (Aux), 1-channel EMC input (Phoenix plug).
4. With 3 levels of priority, with Mic1 having the highest priority, EMC the second priority and the other channels the third priority.
5. 2-channel MICLine input (line input for MIC2/MIC3 channels, sensitivity 775mV).
6. Independent volume knobs for MIC and Aux inputs, total volume knob and treble and bass tone knobs for outputs.
7. Good self-protection against short-circuit, overload and overheating.
8. 2 types of power output: constant voltage output 100V, 70V and constant resistance output 4~16Ω

#### Technical parameters

Model	SA-120U	SA-240U	SA-360U	SA-500U	SA-650U
Power	120W	240W	360W	500W	650W
Power consumption	200W	400W	550W	720W	950W
Sensitivity	Line 250mV Microphone 30mV				
Tone	Bass: ±10dB at 100Hz				
	Treble: ±10dB at 10Hz				
Signal to noise ratio	Line 70dB Microphone 66dB				
Output	70V/100V/4-16Ω				
Frequency	100HZ-18KHZ				
Distortion	< 1%				
Input power	AC 220-240V/50-60Hz				
Size(mm)	484×404×88				
Weight	11.5Kg	13.6Kg	14.6Kg	16.7Kg	17.8Kg