

## SA-240/SA-360/SA-500/SA-650 Mixer Amplifier



### Features:

1. Black brushed panel, 2U/3U rack, 19-inch industrial chassis design.
2. 3-channel microphone input (TRS terminal), 2-channel line input (Aux), 1-channel EMC input (Phoenix plug).
3. With 3-level priority function, in which Mic1 has the highest priority, EMC is the second priority, and other channels are the third priority;
4. 2-channel MIC Line input (line input for MIC2/MIC3 channels with 775 mV sensitivity);
5. MIC and Aux inputs are provided with independent volume adjustment knobs, and outputs are provided with total volume adjustment knobs and treble and bass tone adjustment knobs;
6. The product has short circuit, overload, overheating and other self-protection;
7. Two power output modes: constant voltage output 100 V, 70 V and constant resistance output 4 ~ 16  $\Omega$ .
8. Rated output power: 240W, 360W, 500W, 650W power.

### Technical parameters

Model	SA-240	SA-360	SA-500	SA-650
Power	240W	360W	500W	650W
Power consumption	400W	550W	720W	950W
Sensitivity	Line 250mV Microphone 30mV			
Tone	Bass: $\pm 10$ dB at 100Hz			
	Treble: $\pm 10$ dB at 10Hz			
Signal to noise ratio(A-weighted)	Line 70dB Microphone 66dB			
Output	70V/100V/4-16 $\Omega$			
Frequency	100HZ-18KHZ			
Distortion	< 1%			
Input power	AC 220-240V/50-60Hz			
Size	484×404×88mm			484×404×132mm
Weight	13.5Kg	14.5Kg	16.6Kg	17.7Kg