



2-Zones Mixer Amplifier With USB/SD/FM/Bluetooth

SA-260DU SA-2120DU SA-2180DU



Features

1. Adopts 1206LCD display screen.
2. With 4 unit signal indicator and protection light indicator.
3. With 2-way microphone input, 2-way AUX input.
4. Output impedance is 4-16 Ω , support 2 channels volume adjustment output.
5. Support SD, MP3, FM, Bluetooth 5.0, support power-off memory playback.
6. Supports treble, bass and master volume control

Specification

| | | | |
|-----------------------------|-------------------------|-----------|-----------|
| Model no. | SA-260DU | SA-2120DU | SA-2180DU |
| Rated power | 60W | 120W | 180W |
| Power consumption | 120W | 200W | 230W |
| Output method | 100V/4-16 Ω | | |
| AUX | 400mV-550mV | | |
| MIC | 4mV | | |
| Distortion (THD) | <0.5% at 1KHZ 100V -3dB | | |
| Rated Signal-to-Noise Ratio | >80dB | | |
| Frequency response | 80-20KHz | | |
| Power supply | AC110~220V/50~60Hz | | |
| Fuse | 3.15A | 4A | 5A |
| Size(mm) | 240*88*220mm | | |
| Weight | 9Kg | 11Kg | 13Kg |