

SA-60/SA-120 Mixer Amplifier



Features

1. Black brushed panel, 1U rack, 19-inch industrial chassis design.
2. 3-channel microphone input (TRS terminal), 2-channel line input (Aux), 1-channel EMC input (Phoenix plug);
3. With 3-level priority function, in which Mic1 has the highest priority, EMC is the second priority, and other channels are the third priority;
4. 2-channel MIC Line input (line input for MIC2/MIC3 channels with 775 mV sensitivity);
5. MIC and Aux inputs are provided with independent volume adjustment knobs, and outputs are provided with total volume adjustment knobs and treble and bass tone adjustment knobs;
6. The product has short circuit, overload, overheating and other self-protection;
7. Two power output modes: constant voltage output 100 V, 70 V and constant resistance output 4 ~ 16 Ω .
8. Rated output power: 60W, 120W.

Technical parameters

Model	SA-60	SA-120
Power	60W	120W
Power consumption	100W	200W
Sensitivity	Line 250mV Microphone 30mV	
Tone	Bass: ± 10 dB at 100Hz	
	Treble: ± 10 dB at 10Hz	
Signal to noise ratio(A-weighted)	Line 70dB Microphone 66dB	
Output	70V/100V/4-16 Ω	
Frequency	100HZ-18KHZ	
Distortion	< 1%	
Input power	AC 220-240V/50-60Hz	
Size	484×319×44mm	
Weight	7.2Kg	8.1Kg