

SA-60U Mixer Amplifier With Mp3, Bluetooth And Tuner



Features

1. 2U standard chassis design, aluminum alloy panel, beautiful and practical, the ideal choice for small PA system with optimal cost performance.
2. advanced and efficient power amplifier circuit, with 2 microphone inputs, 3 line inputs and 1 auxiliary output.
3. with 2 levels of priority function, microphone 1 set to the highest priority function, automatically suppress other input signals.
4. each input volume can be controlled independently, with high and low volume adjustment
5. with two modes of constant voltage and constant resistance, constant voltage output is 70V/100V, constant resistance output is 4~16Ω.
6. built-in Bluetooth MP3 decoder and FM tuner module.
7. the device is equipped with abnormal working protection warning function, when the input signal is too large, the load is too heavy, the temperature is too high, the line is short-circuited, the corresponding indicator light prompts, with extremely high reliability.

Technical parameters

Rated power	60W
Output method	70V/100V/4-16Ω
Auxiliary output	600ohms(Ω)/1V(0dBV)
Microphone input	600ohms(Ω),10mV(-54dBV), unbalance
Line input	10Kohms(Ω),775mV(-10dBV), unbalance
Frequency response	60Hz~18KHz
Distortion	<0.1%at1KHz,1/3 Rated power output
Signal-to-noise ratio	Line 70dB Microphone 66dB
Tone	BASS:±10dB(100Hz),TREBLE:±10dB(10KHz)
Protection	ACFUSE; DC VOLTAGE,OVERLOADANDSHORTCIRCUIT
Input power	AC220~240V/50~60Hz
Fuse	4A
Size(mm)	485×340×66
Weight	9Kg