

SA-1012 Eight-in and Eight-out Pre-amplifier



Features

1. With 8 independent input and output amplification channels, each channel can adjust the volume
2. One set of microphone inputs, optionally eight sets of outputs, LED indication
3. With eight groups (zones) arbitrary paging function
4. Microphone input with highest priority, forced cut-in priority function
5. When there is an emergency audio signal input, there is an automatic cut-in priority function.

Technical parameters

Model	SA-1012
Power consumption	20W
Power source	AC220V~240V 50/60HZ
Size	484×390×88mm
Weight	7.5kg