

## SA-240W/SA-360W/SA-500W/SA-650W Power Amplifier



### Features

1. Standard cabinet design (2U), humanized design, exquisite technology, showing high-grade temperament.
2. 1-channel LINE unbalanced TRS input, 1-channel LINE unbalanced TRS cascade output.
3. 1-channel LINE balanced XLR input, 1-channel LINE balanced XLR cascade output;
4. Panel with volume adjustment knob.
5. The product has short circuit, overload, overheating and other self-protection.
6. Two power output modes: constant voltage output 100 V, 70 V and constant resistance output 4 ~ 16 Ω.
7. Input sensitivity selection: 1.4V, 1.0V, 0.775V.

### Technical parameters

Model	SA-240W	SA-360W	SA-500W	SA-650W
Power	240W	360W	500W	650W
Power consumption	400W	520W	750W	900W
Sensitivity	1V			
Signal to noise ratio	>85dB			
Output	70V/100V/240V/4-16Ω			
Input sensitivity	1.4V、1.0V、0.775V			
Frequency	100HZ-18KHZ			
Distortion	<1%			
Size	484×404×88mm			
Net weight	13.4Kg	14.4Kg	16.5Kg	17.6Kg
Weight	15Kg	17.2Kg	19.6Kg	19.9Kg