



## MINI Mixer Amplifier With USB//FM/Bluetooth

### SA-30DU SA-60DU



#### Features

1. It is Class-d Mini amplifier with 30W and 60W for selection, new type D circuit design, all double-sided PCB boards, SMT production process
2. With a metal brushed panel process
3. With 2-way microphone input and 2-way AUX input
4. With high and low tones and master volume control.
5. Support USB/SD/FM/Bluetooth version 5.0, support power-off memory playback.
6. Output low impedance 4-16 ohms.70V,100V. Support DC24V power supply
7. It has over current protection, over voltage protection, high temperature, short circuit protection

#### Specification

Model no.	SA-30DU	SA-60DU
Rated power	30W	60W
Power consumption	60W	90W
Output method	70V/100V/4-16Ω	
AUX/MIC	500mV/10Kohm/1mV/600ohm	
Tone control	Bass:100HZ -+10dB Treble:10KHZ -+10dB	
Distortion (THD)	<0.5% at 1KHZ 100V -3dB	
Rated Signal-to-Noise Ratio	75dB	
Frequency response	100Hz-20KHz	
Power supply	AC110~220V & DC24V/50~60Hz	
Fuse	2A	3.15A
Size(mm)	220*66*200mm (W*H*D)	
Weight	3Kg	