



MINI Mixer Amplifier With USB//FM/Bluetooth

SA-40DU SA-80DU



Features

1. Supports control of treble, bass and master volume.
2. With 1-way microphone input and 2-way AUX input, AUX support MP3 selection.
3. Support USB decoding playback, support for FM/Bluetooth version 5.0, support power-off memory playback.
4. With 1 way auxiliary output, speaker output 4-16 Ω , 100V output.

Specification

Model no.	SA-40DU	SA-80DU
Rated power	40W	80W
Power consumption	80W	110W
Output method	70V/100V/4-16 Ω	
AUX	400mV-550mV	
MIC	4mV	
Distortion (THD)	<0.5% at 1KHZ 100V -3dB	
Rated Signal-to-Noise Ratio	>80dB	
Frequency response	60-20KHz (-1dB)	
Power supply	AC210~240V/50~60Hz	
70V output impedance	122.5 Ω	61.3 Ω
100V output impedance	250 Ω	125 Ω
Fuse	2A	3.15A
Size(mm)	230*65*200mm	
Weight	6Kg	7Kg