



## SD-16-4U 16-Channel Rack Mixer



### Features:

- Compact Multi-function Mixer
- 16-32 low noise channels
- 4 marshalling
- Channel mute function
- 4 auxiliary and flexible fader front and rear selection
- Dual 24 Bit DSP effectors
- 3-channel stereo return
- DJ light
- Each independent 48V phantom power control
- PC USB interface optional
- 19 " Rack Mounting Design

### Technical parameters:

Model	SD-16-4U
Channel	12 Mono + 2 Stereo
Channel equalization	3 Band + Mid Sweep
Auxiliary output	4
Return	3
Effector	24Bit DSP
Main output	1
Grouping output	4
Phantom power	48V DC
Total Harmonic Distortion (THD)	< 0.005%
Noise	-86 dBu
Channel line and microphone	82db
Monitor room output	80db
Effects/Auxiliary Output	80db
Stereo output	82db
Weight	8.00kg
Size mm (H * W * L)	140*474*465mm